



MORSE ET GROUP SECURITY ALARM OPERATION INSTRUCTIONS

Arming the System:

All zones in the system must be closed and after arming the system you have _____ seconds to exit. Enter your 4-digit code and press '**ARM**', the system display will read '**SYSTEM ARMING**'. If any zones are open:

1. The display will read '**X # OF ZONES NOT READY**'.
2. Press the **SCAN** key and the display will tell you where the open zones are located. Once you corrected the open zones re-enter your 4-digit code and press '**ARM**'.

When the system is armed the display will read **SYSTEM ARMED** and will display the numbers of the areas that are activated.

Disarming the System:

Enter your 4-digit code within _____ seconds then press '**clear**'. The number of the group you disarmed will now disappear from the screen. If other areas are still armed, the display will continue to read '**SYSTEM ARMED**' and display the areas that are still activated. If the area you have entered has delayed devices, the keypad may buzz to remind you to disarm the system.

Emergency Buttons:

There are 2 emergency buttons located on the lower right side of the keypad; by pressing both of these keys for about 2 seconds this will cause an audible siren to sound and will send a panic signal to the Central Station. This feature is activated 24 hours even if the alarm system is turned off.

Duress:

If someone would force you to turn the alarm off for any reason, by entering the code _____, you will turn off the alarm and any sirens; but at the same time you are sending a silent panic signal to the Central Station and the police will be dispatched.

Opening & Closing Signals:

These signals are not transmitted until the exit delay has expired. Your keypad will beep for a second when the signal has reached the Central Station to let you know it has transmitted successfully.

WE PROTECT THE THINGS YOU TREASURE

FBN SYSTEMS INC. CENTRAL STATION

(330) 239-1229

Page 1 of 2

Bypassing Zones:

Bypassed zones are not armed areas; they are removed from the monitoring system. This feature should not be abused; it is not a substitute for going and checking the faulty zone. When bypassing any zones the Central Station must be informed prior to removing the zone from the system, this feature causes an alarm signal when activated. When arming the system, if a zone comes up in trouble, while the zone is still displayed, press **'BYPASS'**, and the zone is removed from the system.

X# Alarms Occurred:

The first person that disarms the system after an alarm will get this prompt. While this display is still showing, press the **'MEMORY'** key, this will display the first zone that caused an alarm. If there was more than one zone violated, press **'SCAN'** to show each successive zone.

Reset Smoke Detectors:

Enter a valid code number then press the **'RESET'** key. Once **'RESET'** has been pressed, the **'TATTLE-TALE'** alarm lights on the smoke detectors will be extinguished.

Monitor Mode:

Certain doors have been pre-assigned to cause the keypad to beep if the monitor mode is activated. This feature is to keep track of doors that are out-of-sight to prevent anyone from sneaking in &/or out. To activate this feature, enter a valid code number then press **'MONITOR'**. The display will say **'MONITOR MODE'** when all zones are closed or will scroll all open zones. This feature cannot be used if any of the groups are in an armed condition.

Request Denied:

You may get this prompt if your code is not authorized for the function you are requesting or if some reason the control did not recognize your code. Press **'CLEAR'** twice then retry your code.

History Review:

This system has the capability of storing the last 250 events. To view these events enter a valid code press **'MEMORY'** to show you any alarms in memory, press **'SCAN'** to view each one in order. Pressing **'MEMORY'** twice will show you all the events in memory, press **'SCAN'** to see each one in order. Press **'MEMORY'** three time shows you only the open & close events, press **'SCAN'** to see each even in order.

WE PROTECT THE THINGS YOU TREASURE

FBN SYSTEMS INC. CENTRAL STATION

(330) 239-1229

Page 2 of 2